


400W MODIFIED SINE WAVE DC TO AC POWER INVERTER



» Socket detail please see page 52

Model	CAR400U-121	CAR400U-122	CAR400U-241	CAR400U-242
Rated power	400W			
Surge power	800W (Few seconds)			
Output voltage	110V	230V	110V	230V
Output frequency	50/60Hz ± 3			
No load current draw	≤ 0.3			
Output waveform	Modified Sine Wave 			
USB port	5V 2.1A			
Protection function	Bat. low voltage alarm & shut down, over temperature, over voltage, short circuit, reverse polarity, earth leakage, overload			
Input voltage	12V		24V	
Replaceable fuse	50A × 1		25A × 1	
Cooling fan	By load control			
Dimension	18.5 x 10.8 x 6.2cm (L x W x H)			
N.W./Unit	650g			
QTY/Ctn	20pcs			
Meas./Ctn	45.5 x 34 x 38cm			
Packing	Gift box			
Certification	CE-EMC/LVD, RoHS, E-mark			